

Function Table



SERV TRAYVOU
INTERVERROUILLAGE



Trapped Key
Interlocks



ENERGY



INDUSTRY

In the following table, O/1 defines the position of the key in the lock body.

O: key free or out of the lock body
1: key trapped or in the lock body
L: latch lock

FOR BOLTLOCKS

Function	Lock function							Nb of key	Type	Comments
AA							0	1	Bolt	
AB						0	0	2	Bolt	
AC						1	0	2	Bolt	
AD					0	0	0	3	Bolt	
AE					1	0	0	3	Bolt	
AF					1	0	1	3	Bolt	Only for NS locks, function «&»
AG					1	1	0	3	Bolt	
AH					1	1	1	3	Bolt	
AJ				0	0	0	0	4	Bolt	
AK				1	0	0	0	4	Bolt	
AL				1	1	0	0	4	Bolt	
AM				1	1	1	0	4	Bolt	
AN				1	1	1	1	4	Bolt	
AO			0	0	0	0	0	5	Bolt	
AP			1	0	0	0	0	5	Bolt	
AQ			1	1	0	0	0	5	Bolt	
AR			1	1	1	0	0	5	Bolt	
AS			1	1	1	1	0	5	Bolt	
AT			1	1	1	1	1	5	Bolt	
AU		0	0	0	0	0	0	6	Bolt	
AV		1	0	0	0	0	0	6	Bolt	
AW		1	1	0	0	0	0	6	Bolt	
AX		1	1	1	0	0	0	6	Bolt	
AY		1	1	1	1	0	0	6	Bolt	
AZ		1	1	1	1	1	0	6	Bolt	
BA		1	1	1	1	1	1	6	Bolt	
BB	0	0	0	0	0	0	0	7	Bolt	
BC	1	0	0	0	0	0	0	7	Bolt	
BD	1	1	0	0	0	0	0	7	Bolt	
BE	1	1	1	0	0	0	0	7	Bolt	
BF	1	1	1	1	0	0	0	7	Bolt	
BG	1	1	1	1	1	0	0	7	Bolt	
BH		1	1	1	1	1	0	7	Bolt	
BI		1	1	1	1	1	1	7	Bolt	
BJ	0	0	0	0	0	0	0	8	Bolt	
BK	1	0	0	0	0	0	0	8	Bolt	
BL	1	0	0	0	0	0	0	8	Bolt	
BM	1	1	0	0	0	0	0	8	Bolt	
BN	1	1	1	0	0	0	0	8	Bolt	
BO	1	1	1	1	0	0	0	8	Bolt	
BP	1	1	1	1	1	0	0	8	Bolt	
BQ	1	1	1	1	1	1	0	8	Bolt	

For Access locks

Function	Lock function							Nb of key	Type	Comments
BS							L	1	Latch	
BT						0	L	2	Latch	
BU						1	L	2	Latch	
BV					0	0	L	3	Latch	
BW					0	1	L	3	Latch	
BX					1	1	L	3	Latch	
BY				0	0	0	L	4	Latch	
BZ				0	0	1	L	4	Latch	
CA				0	1	1	L	4	Latch	
CB				1	1	1	L	4	Latch	
CC			0	0	0	0	L	5	Latch	
CD			0	0	0	1	L	5	Latch	
CE			0	0	1	1	L	5	Latch	
CF			0	1	1	1	L	5	Latch	
CG			1	1	1	1	L	5	Latch	
CH		0	0	0	0	0	L	6	Latch	
CI		0	0	0	0	1	L	6	Latch	
CJ		0	0	0	1	1	L	6	Latch	
CK		0	0	1	1	1	L	6	Latch	
CL		0	1	1	1	1	L	6	Latch	
CM		1	1	1	1	1	L	6	Latch	
CN		0	0	0	0	0	L	7	Latch	
CO		0	0	0	0	1	L	7	Latch	
CP		0	0	0	0	1	L	7	Latch	
CQ		0	0	0	1	1	L	7	Latch	
CR		0	0	1	1	1	L	7	Latch	
CS		0	1	1	1	1	L	7	Latch	
CT		1	1	1	1	1	L	7	Latch	
CU	0	0	0	0	0	0	L	8	Latch	
CV	0	0	0	0	0	1	L	8	Latch	
CW	0	0	0	0	1	1	L	8	Latch	
CX	0	0	0	0	1	1	L	8	Latch	
CY	0	0	0	1	1	1	L	8	Latch	
CZ	0	0	1	1	1	1	L	8	Latch	
DA	0	1	1	1	1	1	L	8	Latch	
DB	1	1	1	1	1	1	L	8	Latch	